RADITEK

SATCOM
LNB - Ka Band

LNB, Ka-Band to L Band

N Female, 58dB Gain, Auto Reference

RoHS COMPLIANT

Features:

- 10MHz Reference
- Automatic switch to internal PLL when Ext. Ref. is not available
- LO Stability: ±10, ±25, ±50 KHz in PLL

Order Examples: **RLNB-Ka(17.852-18.588)-L(1052-1788M)-Nf-58d-AR-10-m20**
Description: *(Low Noise Block Down Converter, Ka(17.852-18.588GHz) to L Band(1052-1788MHz), N-Type Female Connector, 58dB Gain, Auto Reference, ±10 KHz LO Stability)*
Additional Options: **Ka(see table below)** **LO Stability: 10, 25, 50**

	A-band	B-band
RF (GHz)	17.852 - 18.588	18.372 - 19.3
LO (GHz)	16.8	17.4
IF (MHz)	1052 – 1788	972 - 1900

Specifications			
Noise figure		1.5	dB Max
LO stability		±10, ±25, ±50 KHz in PLL	
Phase noise		-60 @100Hz -70 @1KHz -80 @10KHz	dBc/Hz
Input VSWR		2.0 :1	
Output VSWR		2.0 :1	
Conversion Gain		58	dB typ
Gain Flatness		±2	dB max
Output P1dB		+5	dBm min
IP3		+15	dBm min
External reference		10MHz, -5 to +5 dBm Automatic switch to internal PLL when Ext. Ref. is not available	
RF input level		-30	dBm max
Spurious	Signal related Power supply related Harmonics	-60 @-10dBm -50 @-10dBm -50 @-10dBm	dBc max
LO leakage (Input)		-37	dBm max
Image rejection		40	dBc min
DC Voltage / Current		+12 to +24	VDC
Input waveguide		WR-42	
Output connector		N-female	
Dimension		104(L) x 60(W) x 39(H)	Mm
Weight		450	g
Operating temperature		-40 to 60	°C

WORLD HQ: 1702L Meridian Ave. Suite 127, San Jose, Ca 95125, U.S.A.
Tel: (408) 266-7404 FAX: (408) 266-4483
WEB: www.raditek.com E-mail: sales@raditek.com

LNB, Ka-Band to L Band

N Female, 58dB Gain, Auto Reference

OUTLINE DRAWING



WORLD HQ: 1702L Meridian Ave. Suite 127, San Jose, Ca 95125, U.S.A.
Tel: (408) 266-7404 FAX: (408) 266-4483
WEB: www.raditek.com E-mail: sales@raditek.com