

Power Amplifier 1.0 MHz to 18.0 GHz, Split Bands Modules Family Data Sheet

Features

- Solid state GaAs/ GaN design
- Instantaneous full bandwidth
- Unconditional stability
- High reliability and ruggedness
- Reverse polarity protection
- Over Temp protection & Alarm



Sizes vary by frequency and power.

5 Years Warranty

Order Example : RAMP-M-9.0-9.6-60d-15230V-Sf-400W-4kW-Pk-L21

Description: (Power Amplifier Module, 9.0-9.6GHz, 60dB gain, 230Vac SMA female Connector, 400Watts, 4kW peak Power)

Typical Specs	
Frequency range	9.0- 9.6 KHz
Peak output Power	4 KW
Avg. power	400Watts
Duty	10.0% max
Pulse width	0.1 to 100 μ sec
PRF	250 Hz to 40 KHz
RF Input power	0 \pm 2 dBm
Small signal (Nominal)	60 dB gain
Output connector	WR 90 with UG 136B / U aluminum
Input/ output VSWR†	1.5:1
Load VSWR	2:1
Near carrier noise	-80dBc/Hz at 100Hz away from the carrier or better
Power Supply Voltage	230V 1Phase or Standard DC line Consumption: 1KW
MTBF	2000 Hrs (min)
Temperature	-10° to +55°C
Humidity (cond)	95 %
Shock & vibration	-30g / 5Grms, 2-200Hz
Altitude	10,000 ft
Cooling system	Forced air cooling
EMI /EMC	MIL STD 461 F

Full Range of Standard Product follows

RAMP-M-1MHz-18GHz-Split Bands Family-L21

Specifications may be subject to change

10/26/17

WORLD HQ: 1702L Meridian Ave. Suite 127, San Jose, Ca 95125, U.S.A.

Tel: (408) 266-7404

FAX: (408) 266-4483

WEB: www.raditek.com

E-mail: sales@raditek.com



Power Amplifier 1.0 MHz to 18.0 GHz, Split Bands Modules Family Data Sheet

Product Range

Class A: Ultra Linear **Class B: Linear**

Note: A detailed data sheet will be provided with every quote.

Freq. Min.	Freq. Max.	Power	Gain	Supply VDC	Class	HS option	Part # RAMP-M-F"low"M-F"High"M-gain dB- Vdc-S(f)- "Power" W Class-(HS option)-L21
(MHz)	(MHz)	(Watts)	(dB)			Heat sink Attached to base	
1	525	10	42	24	AB		RAMP-M-1-525M-42d-24V-Sf-10W-AB-L21
1.5	30	100	17	48	A		RAMP-M-1.5-30M-17d-48V-Sf-100W-A-L21
1.5	30	100	40	48	A	HS	RAMP-M-1.5-30M-40d-48V-100W-A-HS-L21
1.5	30	300	17	48	AB		RAMP-M-1.5-30M-17d-48V-300W-AB-L21
1.5	30	300	40	48	AB	HS	RAMP-M-1.5-30M-40d-48V-300W-AB-HS-L21
5	150	40	50	28	AB		RAMP-M-5-150M-50d-28V-Sf-40W-AB-L21
10	1500	0.003	30	15	A		RAMP-M-10-1500M-30d-15V-Sf-5dBm-A-L21
20	100	200	15	28	AB		RAMP-M-20-100M-15d-28V-Nf-200W-AB-L21
20	500	100	40	50	AB		RAMP-M-20-500M-40d-50V-Sf-100W-AB-L21
20	512	100	40	50	AB		RAMP-M-20-512M-40d-50V-Sf-100W-AB-L21
20	520	40	46	28	AB		RAMP-M-20-520M-46d-28V-Sf-40W-AB-L21
20	1000	2	14	28	A		RAMP-M-20-1000M-14d-28V-2W-A-L21
20	1000	2	50	28	A	HS	RAMP-M-20-1000M-50d-28V-2W-A-HS-L21
20	1000	5	14	28	AB		RAMP-M-20-1000M-14d-28V-5W-AB-L21
20	1000	5	45	28	A		RAMP-M-20-1000M-14d-28V-5W-AB-L21
20	1000	5	50	28	AB	HS	RAMP-M-20-1000M-50d-28V-5W-AB-HS-L21
20	1000	5	45	28	A	HS	RAMP-M-20-1000M-45d-28V-5W-A-HS-L21
20	1000	5	45	28	A		RAMP-M-20-1000M-45d-28V-5W-A-L21
20	1000	5	50	28	AB		RAMP-M-20-1000M-50d-28V-5W-AB-L21
20	1000	10	12	28	A		RAMP-M-20-1000M-12d-28V-10W-A-L21
20	1000	10	14	28	A	HS	RAMP-M-20-1000M-14d-28V-10W-A-HS-L21
20	1000	10	45	28	AB	HS	RAMP-M-20-1000M-45d-28V-10W-AB-HS-L21
20	1000	10	12	28	A		RAMP-M-20-1000M-12d-28V-10W-A-L21
20	1000	20	12	28	AB		RAMP-M-20-1000M-12d-28V-20W-AB-L21
30	512	25	20	48	A	HS	RAMP-M-30-512M-20d-48V-25W-A-HS-L21
30	512	25	30	48	A	HS	RAMP-M-30-512M-30d-48V-25W-A-HS-L21
30	512	50	16	28	A		RAMP-M-30-512M-16d-28V-50W-A-L21
30	512	50	40	28	A	HS	RAMP-M-30-512M-40d-28V-50W-A-HS-L21



Power Amplifier 1.0 MHz to 18.0 GHz, Split Bands Modules Family Data Sheet

Freq. Min. (MHz)	Freq. Max. (MHz)	Power (Watts)	Gain (dB)	Supply VDC	Class	HS option Heat sink Attached to base	Part # RAMP-M-F"low"M-F"High"M-gain dB- Vdc-S(f)- "Power" W Class-(HS option)-L21
30	512	100	20	48	AB		RAMP-M-30-512M-20d-48V-100W-AB-L21
30	512	100	30	48	AB	HS	RAMP-M-30-512M-30d-48V-100W-AB-HS-L21
30	512	100	40	50	AB		RAMP-M-30-512M-40d-50V-Sf-100W-AB-L21
30	512	150	16	28	AB		RAMP-M-30-512M-16d-28V-150W-AB-L21
50	1000	0.1	30	14	A		RAMP-M-50-1000M-30d-Sf-0.1W-A-L21
50	1000	0.25	20	12	A		RAMP-M-50-1000M-20d-12V-0.25W-A-L21
50	1000	5	50	28	A	HS	RAMP-M-50-1000M-50d-28V-5W-A--HS-L21
50	1000	10	14	28	AB		RAMP-M-50-1000M-14d-28V-10W-AB-L21
50	1000	50	50	28	AB		RAMP-M-50-1000M-50d-Sf-50W-AB-L21
50	2500	0.01	20	15	A		RAMP-M-50-2500M-20d-Sf-10dBm-A-L21
50	6000	0.01	19	5.2	A		RAMP-M-50-6000M-19d-Sf-10dBm-A-L21
50	6000	0.1	20	12	A		RAMP-M-50-6000M-20d-12V-0.1W-A-L21
75	140	10	43	24	AB		RAMP-M-75-140M-43d-24V-Sf-10W-AB-L21
88	108	100	20	48	A		RAMP-M-88-108M-20d-48V-100W-A-L21
88	108	100	30	48	A	HS	RAMP-M-88-108M-30d-48V-100W-A-HS-L21
88	108	300	20	48	AB		RAMP-M-88-108M-20d-48V-300W-AB-L21
88	108	300	30	48	AB	HS	RAMP-M-88-108M-30d-48V-300W-AB-HS-L21
100	1000	50	20	28	A		RAMP-M-100-1000M-20d-28V-50W-A-L21
100	1000	50	30	28	A	HS	RAMP-M-100-1000M-30d-28V-50W-A-HS-L21
100	1000	50	50	28	A	HS	RAMP-M-100-1000M-50d-28V-50W-A-HS-L21
100	1000	80	20	28	AB		RAMP-M-100-1000M-20d-28V-80W-AB-L21
100	1000	80	30	28	A		RAMP-M-100-1000M-30d-28V-80W-A-L21
100	1000	80	30	28	AB	HS	RAMP-M-100-1000M-30d-28V-80W-AB-HS-L21
100	1000	80	50	28	A	HS	RAMP-M-100-1000M-50d-28V-80W-A-HS-L21
100	1000	80	50	28	AB	HS	RAMP-M-100-1000M-50d-28V-80W-AB-HS-L21
100	1000	150	30	28	AB	HS	RAMP-M-100-1000M-30d-28V-150W-AB-HS-L21
100	1000	150	50	28	AB	HS	RAMP-M-100-1000M-50d-28V-150W-AB-HS-L21
100	2500	5	10	28	A	HS	RAMP-M-100-2500M-10d-28V-5W-A-HS-L21
100	2500	5	10	28	AB		RAMP-M-100-2500M-10d-28V-5W-AB-L21
100	2500	5	45	28	A	HS	RAMP-M-100-2500M-45d-28V-5W-A-HS-L21
100	3000	0.031	10	5.5	A		RAMP-M-100-3000M-10d-5.5V-Sf-15dBm-A-L21
100	18000	1	33	15	AB		RAMP-M-100-18000M-33d-15V-Sf-1W-AB-L21



Power Amplifier 1.0 MHz to 18.0 GHz, Split Bands Modules Family Data Sheet

Freq. Min. (MHz)	Freq. Max. (MHz)	Power (Watts)	Gain (dB)	Supply VDC	Class	HS option Heat sink Attached to base	Part # RAMP-M-F"low"M-F"High"M-gain dB- Vdc-S(f)- "Power" W Class-(HS option)-L21
200	2000	5	10	48	A		RAMP-M-200-2000M-10d-48V-5W-A-L21
200	2000	20	10	48	AB		RAMP-M-200-2000M-10d-48V-20W-AB-L21
200	2200	25	15	48	A	HS	RAMP-M-200-2200M-25d-48V-25W-A-HS-L21
200	2200	25	30	48	A	HS	RAMP-M-200-2200M-30d-48V-25W-A-HS-L21
200	2200	25	50	48	A	HS	RAMP-M-200-2200M-50d-48V-25W-A-HS-L21
200	2200	50	30	48	A	HS	RAMP-M-200-2200M-30d-48V-50W-A-HS-L21
200	2200	50	50	48	A	HS	RAMP-M-200-2200M-50d-48V-50W-A-HS-L21
200	2200	60	15	48	AB		RAMP-M-200-2200M-15d-48V-60W-AB-L21
200	2200	60	30	48	AB	HS	RAMP-M-200-2200M-30d-48V-60W-AB-HS-L21
200	2200	60	50	48	AB	HS	RAMP-M-200-2200M-50d-48V-60W-AB-HS-L21
200	2200	60	15	48	AB		RAMP-M-200-2200M-15d-48V-60W-AB-L21
200	2200	60	30	48	AB		RAMP-M-200-2200M-30d-48V-60W-AB-L21
200	2200	60	50	48	AB		RAMP-M-200-2200M-50d-48V-60W-AB-L21
200	2200	100	30	48	AB	HS	RAMP-M-200-2200M-30d-48V-100W-AB-HS-L21
200	2200	100	50	48	AB	HS	RAMP-M-200-2200M-50d-48V-100W-AB-HS-L21
225	1000	150	52	50	AB		RAMP-M-225-1000M-52d-50V-150W-AB-L21
300	500	1000	20	50	A	HS	RAMP-M-300-500M-20d-50V-1000W-A-HS-L21
470	860	25	15	48	A		RAMP-M-470-860M-20d-48V-25W-A-HS-L21
470	860	25	40	48	A	HS	RAMP-M-470-860M-40d-48V-25W-A-HS-L21
470	860	100	15	48	AB		RAMP-M-470-860M-15d-48V-100W-AB-L21
470	860	100	40	48	AB	HS	RAMP-M-470-860M-40d-48V-100W-AB-HS-L21
500	2000	100	45	46	AB		RAMP-M-500-2000M-45d-46V-100W-AB-L21
500	2700	125	51	48	AB		RAMP-M-500-2700M-51d-48V-125W-AB-L21
700	1000	25	12	48	AB		RAMP-M-700-1000M-12d-48V-25W-AB-L21
800	4200	15	42	48			RAMP-M-800-4200M-42d-Sf-15W-L21
850	950	5	28	27	AB		RAMP-M-850-950M-28d-27V-5W-AB-L21
910	920	60	48	24	AB		RAMP-M-910-920M-48d-24V-Sf-60W-AB-FM-L21
960	1300	200	53	28	AB		RAMP-M-960-1300M-53d-28V-Sf-200W-AB-L21
960	1300	180	15	28	AB		RAMP-M-960-1300M-15d-28V-Sf-180W-AB-L21
1000	2600	10	12	48	A		RAMP-M-1000-2600M-12d-48V-10W-A-L21
1000	2600	10	40	48	A	HS	RAMP-M-1000-2600M-40d-48V-10W-A-HS-L21
1000	2600	30	12	48	AB		RAMP-M-1000-2600M-12d-48V-30W-AB-L21



Power Amplifier 1.0 MHz to 18.0 GHz, Split Bands Modules Family Data Sheet

Freq. Min. (MHz)	Freq. Max. (MHz)	Power (Watts)	Gain (dB)	Supply VDC	Class	HS option Heat sink Attached to base	Part # RAMP-M-F"low"M-F"High"M-gain dB- Vdc-S(f)- "Power" W Class-(HS option)-L21
1000	2600	30	40	48	AB	HS	RAMP-M-1000-2600M-40d-48V-30W-AB-HS-L21
1000	3000	0.031	50	5//15	A		RAMP-M-1000-3000M-50d-5/15V-Sf-15dBm-A-L21
1000	3000	100	30	50	A	HS	RAMP-M-1000-3000M-30d-50V-Sf-100W-A-HS-L21
1000	6000	75	20	50	A	HS	RAMP-M-1000-6000M-20d-50V-Sf-75W-A-HS-L21
1030	1090	2000	60	50			RAMP-M-1030-1090M-60d-50V-Sf-2kW-L21
1100	1650	0.016	50	12	A		RAMP-M-1100-1650M-50d-12V-Sf-12dBm-A-L21
1100	1700	200	53	50	A		RAMP-M-1100-1700M-53d-50V-Sf-200W-WP-AB-L21
1200	3300	10	20	48	AB		RAMP-M-1200-3300M-20d-48V-10W-AB-L21
1300	1700	100	50	28	AB		RAMP-M-1300-1700M-50d-28V-100-200W-AB-L21
1300	1700	200	50	28	AB		RAMP-M-1300-1700M-50d-28V-100-200W-AB-L21
1500	5900	0.01	15.5	5	A		RAMP-M-1500-5900M-15.5d-5V-Sf-10dBm-A-L21
1800	1900	5	28	27	AB		RAMP-M-1800-1900M-28d-27V-5W-AB-L21
1800	2100	25	12	48	AB		RAMP-M-1800-2100M-12d-48V-25W-AB-L21
1800	2100	25	45	48	A	HS	RAMP-M-1800-2100M-45d-28V-10W-A-HS-L21
1800	4000	10	45	28	AB		RAMP-M-1800-4000M-45d-28V-Sf-10W-AB-L21
1930	2130	5	15	28	A		RAMP-M-1930-2130M-15d-28V-5W-A-L21
2000	2400	0.003	30	15	A		RAMP-M-2000-2400M-30d-15V-Sf-5dBm-A-L21
2000	2600	0.02	45	12	A		RAMP-M-2000-2600M-45d-12V-Sf-13dBm-A-L21
2000	6000	2	12	28	A		RAMP-M-2000-6000M-12d-28V-2W-A-L21
2000	6000	2	40	28	A		RAMP-M-2000-6000M-40d-28V-2W-A-L21
2000	6000	2	40	28	AB		RAMP-M-2000-6000M-40d-28V-2W-AB-L21
2000	6000	2	40	28	A	HS	RAMP-M-2000-6000M-40d-28V-2W-A-HS-L21
2000	6000	6	12	28	AB		RAMP-M-2000-6000M-12d-28V-6W-AB-L21
2000	6000	6	40	28	AB	HS	RAMP-M-2000-6000M-40d-28V-6W-AB-HS-L21
2100	2200	5	28	27	AB		RAMP-M-2100-2200M-28d-27V-Sf-5W-AB-L21
2400	2500	5	28	27	AB		RAMP-M-2400-2500M-28d-27V-Sf-5W-AB-L21
2620	2690	5	28	27	AB		RAMP-M-2620-2690M-28d-27V-Sf-5W-AB-L21
2900	3100	200	63	48			RAMP-M-2900-3100M-63d-48V-200W-2KW-Peak-L21
2900	3300	120	50	48	AB		RAMP-M-2900-3300M-50d-48V-120W-1.2kW-Peak-AB-L21
2900	3300	240	50	48	AB		RAMP-M-2900-3300M-50d-48V-240W-1.2kW-Peak-AB-L21
3000	4000	50	40	28	AB		RAMP-M-3000-4000M-40d-28V-Sf-50W-AB-L21
3000	3500	100	50	28	AB		RAMP-M-3000-3500M-50d-28V-Sf-100W-AB-L21



Power Amplifier 1.0 MHz to 18.0 GHz, Split Bands Modules Family Data Sheet

Freq. Min.	Freq. Max.	Power	Gain	Supply VDC	Class	HS option	Part # RAMP-M-F"low"M-F"High"M-gain dB- Vdc-S(f)- "Power" W Class-(HS option)-L21
(MHz)	(MHz)	(Watts)	(dB)			Heat sink Attached to base	
3500	4000	100	50	28	AB		RAMP-M-3500-4000M-50d-28V-Sf-100W-AB-L21
3600	4300	10	15	50	AB		RAMP-M-3600-4300M-15d-50V-Sf-10W-AB-L21
3900	5500	20	10	28	AB		RAMP-M-3900-5500M-10d-28V-Sf-20W-AB-L21
5000	20000	0.1	18	5.5	A		RAMP-M-5000-20000M-18d-Sf-16dBm-A-L21
6000	7000	50	40	28	AB		RAMP-M-6000-7000M-40d-28V-Sf-50W-AB-L21
6000	12000	100	42	46	AB		RAMP-M-6000-12000M-42d-46V-Sf-100W-AB-L21
6000	18000	0.31	27	12	A		RAMP-M-6000-18000-27d-12V-Sf-25dBm-A-L21
6000	18000	1.58	33	15	A		RAMP-M-6000-18000M-33d-15V-Sf-32dBm-A-L21
7950	8550	0.01	30	15	A		RAMP-M-7950-8550M-30d-Sf-10dBm-A-L21
8500	10500	15	30	12	AB		RAMP-M-8500-10500M-30d-15Wi-Sf-AB-L21
9100	9600	400	56	40	AB		RAMP-M-9100-9600M-56d-40V-Sf-400W-AB-L21
9200	9600	100	56	50	AB		RAMP-M-9200-9600M-56d-50V-Sf-100W-AB-L21
9200	9600	200	56	50	AB		RAMP-M-9200-9600M-56d-50V-Sf-200W-AB-L21
12000	18000	10	40	28	AB		RAMP-M-12000-18000M-40d-28V-Sf-10W-AB-L21